## Two-Way Intercom Button (PART NUMBER: EA2WIB)




The EverAlert intercom button provides reliable, hands-free communication for PoE-enabled SIP VoIP phone systems. The unit can be programmed from any touch-tone phone, a PC on the same LAN, or remotely using a static IP address, and can dial up to five programmable numbers.

A "Call" LED flashes during dialing and illuminates when the call is answered. All programming parameters, including phone numbers, are stored in non-volatile memory, eliminating the need for batteries. The EA2WIB is powered via PoE.

### FEATURES

- 2 Amp relay contacts for door / gate or Strobe Light (DOD 242) control
- Blue "Call Connected" LED indicator
- SIP compliant (see Product Manual for list of compatible IP-PBX phone systems)
- PoE powered (class 1, <4 Watts)
- Automatic Noise Canceling (ANC) feature for proper operation in noisy environments
- VoIP audio detection eliminates the need for "Push to Talk" mode
- Handsfree operation
- T-10 Torx security screws for added security
- Programmable to dial up to 5 numbers
- Cycles through backup phone numbers on busy or ring-no-answer
- Hangs up on busy signal, time-out or touch tone command
- Programming software included
- Network downloadable firmware
- Remotely programmable
- Diagnostics for testing mic, speaker, and relay
- Flush mounts with a double gang electrical box (not included)
- Extended temperature range: -40°F to 140°F (-40°C to 60°C)

### ORDERING INFORMATION

| Part # | Description |
|---|---|
| EA2WIB | Two-Way Intercom Button |

At American Time, we continually strive to improve our products to meet our customers' needs and to provide the best possible value. The above specifications are believed to be correct, are subject to change without notice and may otherwise vary from the above. Please call if you need verification of any specifications or the suitability of a particular product for a particular application.
© American Time